

High Pressure Sodium Lamp Ballast

บัลลาสต์สำหรับหลอดโซเดียมความดันสูง



Product Description: This is the one of ballast that use for High Pressure Sodium Lamp

Feature:

- Each High Pressure Sodium Lamp Ballast produced from high quality silicon steels and the best enamel for copper wire which can bear up to 200 Degree Celsius
- Designed for building and huge construction
- Suitable for heavy usage continuously
- Long lifetime usage of the lamp
- Easy for installation and cabling
- Five years guarantee from our company

บัลลาสต์ GATA สำหรับหลอดโซเดียมความดันสูงเป็นบัลลาสต์สำหรับหลอดโซเดียมที่ผลิตมาเพื่อใช้ในงานส่องสว่างสำหรับถนนหนทาง และในอาคารสำหรับจุดที่ต้องการความชัดเจนของการสังเกต บัลลาสต์ GATA นั้นผลิตจากวัตถุดิบที่มีคุณภาพดีจึงเหมาะกับการใช้งานอย่างต่อเนื่องทุกวัน โดยมีการออกแบบให้ช่วยลดอุณหภูมิความร้อนสูงถึง 200 องศาเซลเซียสจึงเหมาะกับทุกสภาพการใช้งาน




Figure A




Figure B




Figure C

Item Description Ballast	Lamp			P.F.C. Cap. (µF)	Supply (Volt/Hz)	Dimension (mm)				Weight (kg)	PF	Figure	Certification
	Watt (W)	Current (A)	Volt (V)			A	B	C	D				
N35	35	0.53	90	6.00	220/50	30	66	112	54	0.90	0.35	A	TIS 1965-2542 TIS 673-2530 Acc. to IEC 60922 IEC 60923
N70	70	1.00	85	12.00	220/50	40	66	112	54	1.20	0.37	A	
N100	100	1.20	100	12.00	220/50	40	66	112	54	1.25	0.42	A	
N150	150	1.80	100	18.00	220/50	75	66	145	54	2.10	0.39	A	
N250	250	3.00	100	32.00	220/50	72	75	153	64	2.75	0.39	A	
N400	400	4.45	105	50.00	220/50	60	107	135	88	4.15	0.43	B	
N1000	1000	10.30	110	100.00	220/50	140	107	220	88	8.90	0.44	B	
N2000	2000	10.30	230	50.00	380/50	96.5	152	195	130	15.7	0.56	C	
N2000	2000	8.80	245	40.00	380/50	96.5	152	195	130	15.3	0.63	C	
N2000	2000	10.30	230	50.00	400/50	96.5	152	195	130	15.7	0.56	C	
N2000	2000	8.80	245	40.00	400/50	96.5	152	195	130	15.3	0.63	C	